

## DC24V Bus audio amplifier for coach and Bus



1. IDIN standard installation dimensions
2. use international famous Kara OK Chip
3. Support for high-frequency wireless Kara OK function, raise the shouting effect .
4. support 4-way 6.35 microphone interface
5. independent power amplifier, maximum power output 4 \* 45W
6. two-way audio output
7. two-way audio input
8. support external audio mute function
9. support audio track of external player to switch
10. Input Voltage: 12VDC-32VDC
11. output voltage: 12VDC
12. Maximum Output Power: 120W

Item No.	BM-1
Product name	24V Bus audio amplifier special for coach and bus
Power input	DC12V-36V
Power output	DC12V
Output current	≤10A
Ripple voltage	<100mV
No-load current	<60mA
Reverberation time	2.3s(adjustable)
Frequency	600~900MHZ
Noise ratio	≥80dB
THD	≤0.03%

Channel separation	>60dB
Impedance	100k
Maximum active power	30w*4
Input sensitivity	200mv
Product dimension	178mm*50mm*155mm
Net weight	1.2kg
Gross weight	1.5kg
Packing	10pcs/CNT, CNT box size: 49.5*29.2*43.2cm, G.W: 16.5kg

## Package:

- 1\* Bus amplifier
- 1\* Remote controller
- 1\* Convert cable
- 1\* User manual